



# North Florida Communications

[www.northfloridacommunications.com](http://www.northfloridacommunications.com)

[www.ournewphone.com](http://www.ournewphone.com)

---

## **LG ipLDK-60 Programming Flexible Buttons**

- 1) Press the “Trans/PGM” button.
- 2) Press the Flexible Button you wish to program
- 3) To program a Direct Station Select button simply dial the 3 Digit Extension number you wish to program, or select a feature code from the chart below.
- 4) Press “Hold/Save” to store your selection
- 5) Return to Step 2 to program another Flexible Button or press “Speaker” to quit.

Numbering Plan for 24-button Digital Phone			
Account Code	PGM + 80	MPB Version Display	PGM + 72
Alarm Reset	565	Record Page MSB	PGM + 65
Auth. Code Change	PGM + 32	Record User Greeting	PGM + 61
Auth. Code Register	PGM + 31	Record User Name	PGM + 6*
Background Music	PGM + 73	Register Station Name	PGM + 74
Call Coverage	PGM + 46	Record User Greeting	PGM + 61
Call Log	PGM + 57	Register Station Name	PGM + 74
Call Park	601-608	REDIAL button	PGM + 97
Camp-On	PGM + 85	Ring Answer Mode	PGM + 12
COS Down	PGM + 21	Ring Type	PGM + 11
COS Restore	PGM + 22	Set Custom MSG	PGM + 52
Direct Station Select	100-147	Set Pre-selected MSG	PGM + 51
E-mail Notification	PGM + 60	Set Wake-up Time	PGM + 41
Erase Page MSG	PGM + 67	Speaker/Headset	PGM + 75
Erase User Greeting	PGM + 66	Two Way Recording	PGM + 54
Erase User Name	PGM + 6#	Universal Night Ans	569
Group Call Pickup	PGM + 71	Wake-up Disable	PGM + 42
H-T-P	PGM + 12	Walking COS	PGM + 23
Headset Ring Mode	PGM + 76	Outside Line Access	
Hunt Group	620-629	Group	801-808
ICM Hold	PGM + 83	Group Access	9
LCD Display Language	PGM + 71	Individual Line Access	8801-8812
Listen Station Number	PGM + 63	Speed Dial	
Listen Station Status	PGM + 65	Station Speed Dial	SPEED + 000-099
Listen Time & Date	PGM + 62	System Speed Dial	SPED + 2000-2449
Loop Button	PGM + 84	Ring Answer Mode	PGM + 12